# CONTROL4 LUX DUAL DIMMER SWITCH KEYPAD



### **CONTROL4 LUX DUAL DIMMER SWITCH KEYPAD** C4-L-CDSW

The Control4 Dual Dimmer Switch Keypad seamlessly combines dimming and switching with a customizable keypad, delivering superior lighting control for up to two loads. Elegantly manage multiple functions—such as adjusting both a bathroom fan and light—using a single, space-saving device.

#### Features

- Control two loads, one dimmable and one non-dimmable with one device
- Fully configurable keypad interface
- Available with premium metal faceplates and a variety of stylish colors and finishes
- Combines elegant dimming with a configurable keypad for the ultimate in lighting control of up to two lighting loads
- Unlock the power of one-touch automation by simply replacing an existing light switch with a wireless dimmer
- Zigbee 3.0



# CONTROL4 LUX DUAL DIMMER SWITCH KEYPAD

C4-L-CDSW
120-240V AC +/- 10% 50/60 Hz
Load 1 (dimmer): No, when dimming load is used. Load 2 (switch): Yes, if using only switched load.
120V: 1.90W all LEDs off, 2.64W all LEDs on 240V: 4.20W all LEDs off, 4.93W all LEDs on
<b>Dimming:</b> Incandescent, halogen, electronic (solid state) low voltage (ELV) transformers, magnetic (iron core, inductive) low voltage (MLV) transformers, LEDs
Switch Mode: above load types and also motors
Incandescent: 150W, LED: 80W
Incandescent: 240W, LED: 80W
Incandescent: 1/25A/150W, LED: 1.25A/150W, MLV: 50W, Flourescent: 50W, Motor: 1.25 FLA, 7.5 LRA
Incandescent: 1/25A/300W, LED: 1.25A/300W, MLV: 50W, Flourescent: 50W, Motor: 1.25 FLA, 7.5 LRA
0 to 40°C (32 to 104°F)
5% to 95% non-condensing
-20 to 70°C (-4 to 158°F)

Miscellaneous				
Control Communications	Zigbee 3.0, IEEE 802.15.4, 2.4 GHz, 15-channel spread spectrum radio			
Wallbox volume	5.75 cubic inches			
Lighting scenes per device	127 maximum			
Actions per device	15 maximum per lighting scene			
Weight	0.05 kg (0.12 lb.)			
Shipping Weight	0.08 kg (0.18 lb.)			
Compatible Color Kits	C4-L-CKKC-XX or C4-L-CKUDIMSWITCH-XX			



# CONTROL4 LUX DUAL DIMMER SWITCH KEYPAD







#### AVAILABLE BUTTON SIZES

All keypads include 6 button "slots" to accommodate different button types and sizes. This setup allows for a flexible and customizable approach to your keypad design, making it easy to tailor the configuration to your specific needs.



#### **Special Features**

- Rocker buttons can be utilized in any keypad configuration and will occupy all 6 slots.
- The motion dimmer feature requires a unique configuration: it includes a 5 high button and a single high motion lens occupying the last slot.



## POPULAR BUTTON CONFIGURATIONS



6 buttons of 1 high



2 buttons of 3 high



5 buttons of 1 high plus one up/down button



Combination of 2 high and 4 single high buttons



3 buttons of 2 high



Combination of 2 high and 3 single high buttons plus one up/down button

## GANG PLATE CONFIGURATIONS



1 gang



2 gang



3 gang



4 gang

Control



# **CONTROL4** LUX COLORS AND FINISHES

		· · · · ·					
WHITE (WH)	SNOW WHITE (SW)	BISCUIT (BI)	LIGHT ALMOND (LA)	TAUPE (TP)	LIGHT GRAY (LG)		
·       · <t< th=""><th>TONE GRAY (SG)</th><th>COFFEE (CF)</th><th>MIDNIGHT BLACK (MB)</th><th>BLACK (BL)</th><th></th></t<>	TONE GRAY (SG)	COFFEE (CF)	MIDNIGHT BLACK (MB)	BLACK (BL)			
ANTIQUE BRASS (BS)	ANTIQUE BRONZE (BZ)	ASH GRAY (AG)	CHROME	MATTE STAINLESS	SATIN BRONZE		
(BS)	(BZ)	<ul> <li>(AG)</li> <li>(CH)</li> <li>(MS)</li> <li>(SB)</li> </ul> Closs colors White, Light Almond, Black Matte colors Snow White, Biscuit, Taupe, Light Gray, Stone Gray, Aluminum, Coffee, Midnight Black Metallic colors Antique Brass, Antique Bronze, Ash Gray, Chrome, Matte Stainless, Satin Bronze, Satin Nickel, Venetian Bronze					

Control